

Ei408



RadioLINK Switched Input Module



- Triggers the alarms in a system if an external device is activated, such as a sprinkler flow switch
- 10 year Lithium battery powered
- RadioLINK Wireless interconnection
- 5 year guarantee



Description

The Ei408 RadioLINK Switched Input Module will trigger wirelessly interconnected alarms if an external device is activated, such as a sprinkler system. It is powered by a 10 year sealed in lithium cell giving a completely wire free installation

Technical

RF Frequency (MHz)	868.499	RF Range (m)	>100 in free air
Indicators	Green - Power / Red - House code / Amber - EoL	Battery Type	Lithium primary
Technologies	RadioLINK		

Dimensions & Weights

Depth (mm)	52	Height (mm)	92
Width (mm)	92	Product weight (kg)	0.166
Packaged weight (kg)	0.193		

Approvals & Warranty

Warranty	5 year warranty	EAN Number	5099383003567
-----------------	-----------------	-------------------	---------------

Environmental

Humidity Range (%)	0-95	Temperature Range (°C)	-10 to 40
---------------------------	------	-------------------------------	-----------